



Main

Product or component type	Load Center
Range of product	Homeline
Load center type	Main lugs
Line Rated Current	50 A
Number of spaces	2
Number of circuits	4
NEMA degree of protection	NEMA 3R outdoor
Cover type	Surface cover
Provided equipment	Circuit breaker (1) 2P 50 A 120/240 V AC ready assembled

Complementary

Short-circuit current	10 kA
Phase	1 phase
System Voltage	120/240 V AC
AWG gauge	AWG 8...AWG 6 (aluminium/copper)
Wiring configuration	3-wire
Cover finish	Gray baked enamel
Enclosure material	Welded galvanized steel
Surface finish	Baked enamel grey
Box number	1R
Height	9.37 in (238 mm)
Width	4.88 in (124 mm)
Depth	4.02 in (102 mm)

Environment

product certifications	UL CSA
------------------------	-----------

Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 1248 - Schneider Electric declaration of conformity	Compliant - since 1248 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Need no specific recycling operations	Need no specific recycling operations
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds which is known to the State of California to cause cancer and birth defects or other reproductive harm.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.